




KNURLED CYLINDRICAL THREADED INSERTS, CLOSED END TYPE  
 BLINDNIETMUTTERN RUNDSCHAFT GERÄNDELT SCHAFTENDE GESCHLOSSEN  
 INSERTS FILETÉS CRANTÉS CYLINDRIQUES BORGNES  
 TUERCAS REMACHABLES CILINDRICAS ESTRIDADAS CIEGAS


STAINLESS STEEL  
 EDELSTAHL  
 ACIER INOX INOX




**A2**

KNURLED UNDERNEATH THE  
 HEAD


| CODICE<br>CODE               |  | S<br>GRIP              | D<br>+0,07/-0,1 |  | T<br>+/-0,3 | K<br>+/-0,15 | L<br>+/-0,3  | I<br>~     |  |
|------------------------------|---|------------------------|-----------------|---|-------------|--------------|--------------|------------|---|
|                              |   |                        |                 |   |             |              |              |            | Nm  |
| 03TPBFR-XFI<br>03TPB-LFR-XFI | M3  | 0,5 - 2,5<br>2,5 - 4,0 | 4,9             | 5   | 8           | 0,9          | 13<br>16,5   | 10<br>11   | 2   |
| 04TPBFR-XFI<br>04TPB_LFR-XFI | M4  | 0,5 - 3,0<br>3,0 - 4,5 | 5,9             | 6   | 9           | 1            | 16,5<br>18   | 11<br>12   | 5   |
| 05TPBFR-XFI<br>05TPB_LFR-XFI | M5  | 0,5 - 3,0<br>3,0 - 5,5 | 6,9             | 7   | 10          | 1            | 19<br>21,5   | 12<br>14   | 8,5   |
| 06TPBFR-XFI<br>06TPB_LFR-XFI | M6  | 0,5 - 3,0<br>3,0 - 5,5 | 8,9             | 9   | 13          | 1,5          | 22<br>24,5   | 16<br>18   | 15  |
| 08TPBFR-XFI<br>08TPB_LFR-XFI | M8  | 0,5 - 3,0<br>3,0 - 5,5 | 10,9            | 11  | 16          | 1,5          | 26,5<br>29   | 19<br>21   | 26  |
| 10TPBFR-XFI<br>10TPB_LFR-XFI | M10   | 0,5 - 3,0<br>3,0 - 6,0 | 12,9            | 13  | 17          | 2            | 28,5<br>33,5 | 20,5<br>24 | 50  |




FLAT HEAD  
 FLACHKOPF  
 TÊTE CYLINDRIQUE  
 CABEZA PLANA



| CODICE<br>CODE |  | S<br>GRIP | D<br>+0,07/-0,1 |  | T<br>+/-0,3 | K*<br>+/-0,15 | L<br>+/-0,3 | I<br>~ |  |
|----------------|--|-----------|-----------------|--|-------------|---------------|-------------|--------|--|
|                |  |           |                 |  |             |               |             |        | Nm   |
| SB3AFR-XFI     | M3   | 0,5 - 2,5 | 4,9             | 5  | 6           | 0,8           | 15,5        | 11     | 2  |
| SB4AFR-XFI     | M4   | 0,5 - 3,0 | 5,9             | 6  | 7           | 0,8           | 16,5        | 12,5   | 3  |
| SB5AFR-XFI     | M5   | 0,5 - 3,0 | 6,9             | 7  | 8           | 0,8           | 19          | 15     | 6  |
| SB6AFR-XFI     | M6   | 0,5 - 3,0 | 8,9             | 9  | 10          | 0,8           | 22          | 16     | 11   |
| SB8BFR-XFI     | M8   | 0,5 - 3,0 | 10,9            | 11   | 12          | 0,8           | 25          | 18,5   | 20   |
| SB10AFR-XFI    | M10  | 0,8 - 3,5 | 12,9            | 13   | 14,5        | 1             | 30          | 21     | 32   |
| SB12AFR-XFI    | M12  | 0,8 - 4,0 | 15,9            | 16   | 17,6        | 1             | 31,5        | 22,5   | 50   |

REDUCED COUNTERSUNK HEAD  
 KLEINER SENKKOPF  
 TÊTE RÉDUITE  
 CABEZA REDUCIDA



| CODICE<br>CODE |  | S<br>GRIP | D<br>+0,07/-0,1 |  | T<br>+/-0,3 | K<br>+/-0,15 | L<br>+/-0,3 | I<br>~ |  |
|----------------|---|-----------|-----------------|---|-------------|--------------|-------------|--------|---|
|                |   |           |                 |   |             |              |             |        | Nm  |
| 03TFBFR-XFI    | M3  | 1,5 - 3,0 | 4,9             | 5   | 8           | 1,7          | 16,5        | 11     | 2   |
| 04TFBFR-XFI    | M4  | 1,5 - 4,0 | 5,9             | 6   | 9           | 1,7          | 17,5        | 12,3   | 3   |
| 05TFBFR-XFI    | M5  | 1,5 - 4,0 | 6,9             | 7   | 10          | 1,7          | 20,5        | 14,5   | 6   |
| 06TFBFR-XFI    | M6  | 1,5 - 4,5 | 8,9             | 9   | 12          | 1,7          | 23,5        | 17,5   | 11  |
| 08TFBFR-XFI    | M8  | 1,5 - 4,5 | 10,9            | 11  | 14          | 1,7          | 28          | 18,5   | 20  |
| 10TFBFR-XFI    | M10   | 2,0 - 4,5 | 12,9            | 13  | 16          | 1,7          | 30,5        | 20,5   | 32  |
| 12TFBFR-XFI    | M12   | 2,0 - 4,5 | 15,9            | 16  | 19          | 1,7          | 31,5        | 21     | 50  |

COUNTERSUNK HEAD  
 SENKKOPF  
 TÊTE FRAISÉE  
 CABEZA AVELLANADA

